


F R E E J A C K

FreeJack 4" Round Flush Canopy LED LED

DESCRIPTION

Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformer (included) fits in junction box. One FreeJack port. for ceiling or wall. Driver wattage. LED 60W.



INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. For ceiling or wall. If wall mounting, head should be no longer than 6".



OTHER

For use with any 12 volt FreeJack pendant or head (sold separately).

WEIGHT

8-8lb / 3.63-3.63kg ±



freejack 4" round
flush canopy led

ORDERING INFORMATION

700FJ4RF SHAPE OR SIZE	FINISH	VOLTAGE
4" ROUND INTEGRAL TRANSFORMER	R AGED BRASS	-LED 120V IN/12V OUT LED
	Z ANTIQUE BRONZE	- 277V IN/12V OUT LED
	B BLACK	LED277
	C CHROME	
	S SATIN NICKEL	
	W WHITE	



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700FJ4RF _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2019 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.